LTECH

DMX512 DECODER

LT-912-OLED

12 CHANNELS

OLED display
8 bit / 16 bit
3 kinds of DMX interfaces
Dimming Curve: 0.1~9.9
Shortcut / Over load protection

RDM ⇄ DMX

Photoelectric Isolation



www.ltech-led.com

Product Introduction:

1. Designed for Hi-power multiple channels application, 12 channels output, and Max. 4A current per channel, up to 1152W output power.
2. Easy operation with OLED screen and the touch buttons.
3. 3 kinds of mode optional: single color, color temperature, RGB.
4. Support 3 kinds of DMX ports with signal isolation function: 5-pin XLR, RJ45 and green terminal (with signal amplifier function).
5. With RDM remote management protocol, the operations can be completed via the RDM master console, such as parameters browsing & setting, DMX address setting, equipment recognition, etc.
6. With photoelectric isolation function.
7. With shortcut protection and over load protection, as well as warning function when fault.
8. With fast self-testing function.
9. 16bit (65536 levels) / 8bit (256 levels) grey level optional.
10. Multiple dimming curve (0.1~9.9) optional.



5-pin XLR | RJ45 | RDM | Photoelectric Isolation | Shortcut Protection | Over load Protection | Display

Technical Specs:

Model :	LT-912-OLED
Input Signal :	DMX512/RDM
Input Voltage :	12~24Vdc
Current Load :	4A × 12CH Max 48A
Output Power :	(0~48W...96W) × 12CH Max. 1152W
DMX Interface :	5-pin XLR, RJ45, Green terminal
Control Mode :	Dimming/CT/RGB
Dimming Curve :	0.1~9.9
Grey Level :	8bit (256 levels) / 16bit (65536 levels)
Photoelectric Isolation :	Yes
Protection:	Shortcut / Over load
Working Temperature :	-30℃~65℃
Dimensions :	L180×W122×H39mm
Package Size :	L193×W127×H41mm
Weight (G.W.) :	730g

FC CE RoHS warranty 5 years ISO9001:2008

Product Size:

Unit: mm



Main Component Description:







OLED Screen Interface:

Press "M" key, switch entries.
Long press "M" key, back to main page.
Press "∧" or "∨" key, parameter adjustment.
Exit: back to previous page.

1. DMX Address Setting



Main page

Press "∧" or "∨" key to set DMX address.
Range: 001~512

2. PWM Frequency

Press "∧" or "∨" key to choose.

Optional :
Std (standard)
High
Mid (middle)
Low

No flicker in video camera.

Smooth and delicate, human eye is comfortable.

✻ It is recommended to use standard.

3. Mode



Press "∧" or "∨" key to choose.
Optional : Dim
CT
RGB

4. Grey Level

Press "∧" or "∨" key to choose.
Optional : 8bit
16bit (choose it if the master controller support this function)

5. Dimming Curve



Press "∧" or "∨" key to choose.
Optional : Standard
Linear
0.1~9.9

It is recommended to use standard, 0.1-9.9 is for special requirements.

6. Enhance dimming



Press "∧" or "∨" key to choose.
Optional : Std (standard)
Smo (smooth)

✻ It is recommended to use standard.

Smo: This option with smooth processing, realize the dimming flicker-free and dynamic effects more downy.

7. Tool



✻ Fast self-testing function: press "∧"or "∨" keys simultaneously for 2-3 seconds under any page, decoder will enter self-testing function.

Wiring Diagram:

1. DMX console connection:



LT-912-OLED is equipped with 3 types DMX terminals for users' selection. The following diagram takes 5-pin XLR as an example, same connecting method for the rest two: RJ45 & green terminal (with amplifier function).

* If the recoil effect occurs because of longer signal line or bad line quality, please try to connect 0.25W 90-120Ω terminal resistor at the end of each line.

2 Connecting LED lights:





Dimming Mode



CT Mode



RGB Mode



3. The connection diagram of 3 kinds of DMX/RDM terminals:



5-pin XLR Connected in Parallel



Green Terminal Connected in Parallel



RJ45 Connected in Parallel

These 3 terminals can be connected in a mixed way.

✻**Installation Attention :** please reserve enough ventilation distance between decoders (>20mm), be sure not to block the vent, or will affect lifetime of decoder for poor heat dissipation.

4. The connection diagram of AMP signal amplifier terminal:

* Connecting with green terminal or an extra amplifier will be needed when more than 32 decoders are connected or use overlong signal wire(as shown below).
Signal amplifier should not be more than 5 times continuously.



Address setting table

Mode		DIM	CT	RGB
Address Quantity		4	8	12
Resolution		8bit	8bit	8bit
Channel	1	001	001	001
	2	001	002	002
	3	001	002	003
	4	002	003	004
	5	002	004	005
	6	002	004	006
	7	003	005	007
	8	003	006	008
	9	003	006	009
	10	004	007	010
	11	004	008	011
	12	004	008	012

Mode		DIM	CT	RGB
Address Quantity		8	16	24
Resolution		16bit	16bit	16bit
Channel	1	001 002	001 002	001 002
	2	001 002	003 004	003 004
	3	001 002	003 004	005 006
	4	003 004	005 006	007 008
	5	003 004	007 008	009 010
	6	003 004	007 008	011 012
	7	005 006	009 010	013 014
	8	005 006	011 012	015 016
	9	005 006	011 012	017 018
	10	007 008	013 014	019 020
	11	007 008	015 016	021 022
	12	007 008	015 016	023 024

Update Time: 2017.04.20_A1