

SKU code	URSMART
Voltage	DC 12/24V
Output Current	6 Amp Per Channel
Max Output	15 Amp
Transmission Type	RF 2. 4GHz
Communication Mode	WiFi-IEEE 802.11b/g/n 2.4GHz
Transmission Frequency	2400-2483.5MHz
Transmission Power	6dBm
Control Distance	30 Metres (without obstructions)
Diming Range	1~100%
Colour Control	Single/CCT/RGB/RGBW/RGBCCT
IP Rating	IP20
Operating Temperature	-20°C ~ +60°C
Dimensions (L*W*D)	125mm x 38mm x 25mm
Certification	CE-EMC CE-LVD ROHS
Warranty	3 years

Ready To Connect Smart WiFi App Controlled Receiver

The 5-in-1 receiver is a perfect solution for any LED strip lighting you want to control. Easily synchronize with the Amazon Alexa or Gogle Assisstant for seamless voice controlled lighting.

This controller can be used with Single colour, CCT, RGB, RGBW & RGB CW+WW LED tapes. Extremely versatile, simply download the app for iOS or Android. The app can be used without Amazon Alexa as a standalone Wifi or 2.4GHz RF controlled lighting solution.

The app is feature packed with different lighting effects as well as standard controlling methods such as dimming. Also features a timer function so your lights